

MCB 1P 6/10kA C-3A 1M

Product Datasheet

	nite		

Architecture	
Number of protected poles	1
Number of poles	1 P
Type of pole	1 P
Curve	С
Functions	
Concurrently switching N-neutral	no
Connectivity	
Top connection alignement for modular devices	Aligned terminal
Bottom connection alignement for modular devices	Aligned terminal
Main electrical features	
Rated short circuit breaking capacity Icn AC according IEC60898-1	6 kA
Rated operational voltage Ue	230 / 400 V
Frequency	50/60 Hz
Voltage	
Rated insulation voltage	500 V
Rated impulse withstand voltage	4000 V
Electric current	
Rated current	3 A
Rated service breaking capacity Ics AC according IEC 60898-1	6 kA
min/maxi threshold value of the AC thermal operation	1,13 / 1,45 ln
Magnetic regulating currrent	5 / 10 ln
min/maxi threshold value of the DC magnetic operation	7 / 15 ln
min/maxi threshold value of the DC thermal operation	1,13 / 1,45 ln
Breaking capacity on 1 pole for IT 400V NF 60947-2	3 kA
Rated short circuit breaking capacity Icn under 230V AC according IEC60898-1	6 kA
Rated ultimate short-circuit breaking capacity Icu under 230V AC IEC 60947-2	10 kA
Rated ultimate short-circuit breaking capacity Icu	10 kA

under 415V AC IEC 60947-2



Electric current / temperature	
Rating current -25°C	3,3 A
Rating current -20°C	3,3 A
Rating current -15°C	3,2 A
Rating current -10°C	3,2 A
Rating current -5°C	3,2 A
Rating current 0°C	3,2 A
Rating current 5°C	3,1 A
Rating current 10°C	3,1 A
Rating current 15°C	3,1 A
Rating current 20°C	3,1 A
Rating current 25°C	3 A
Rating current 30°C	3 A
Rating current 35°C	3 A
Rating current 40°C	2,9 A
Rating current 45°C	2,9 A
Rating current 50°C	2,9 A
Rating current 55°C	2,9 A
Rating current 60°C	2,8 A
Rating current 65°C	2,8 A
Rating current 70°C	2,8 A
Current correction factors	
Correction factor of rating current for 2 devices placed side-by-side	1
Correction factor of rating current for 3 devices placed side-by-side	0,95
Correction factor of rating current for 4 and 5 devices placed side-by-side	0,9
Correction factor of rating current for 6 devices placed side-by-side	0,85
Correction factor of magnetic tripping with 100 Hz	1,1
Correction factor of magnetic tripping with 200 Hz	1,2
Correction factor of magnetic tripping with 400 Hz	1,5
Correction factor of magnetic tripping with 60 Hz	1
Frequency	
Frequency	50 to 60 Hz
Power	
Total power loss under IN	1,9 W
Power loss per pole at In	1,9 W
Endurance	
Electric endurance in number of cycles	4000
Number of mechanical operations	20000



0 mm 3 mm 5 mm screw 2,8Nm
5 mm screw 2,8Nm
screw 2,8Nm
2,8Nm
2,8Nm
•
NA
etallic
nnect
no
no
yes
5 mm²
5 mm²
screw
898-1
erned
IP20
.70 °C
2
3
000 m
000 m mates